

CP-X9110/CP-WX9210/CP-WU9410

User's Manual (detailed)

Operating Guide – Technical

Example of computer signal

Resolution (H x V)	H. frequency (kHz)	V. frequency (Hz)	Rating	Signal mode
720 x 400	37.9	85.0	VESA	TEXT
640 x 480	31.5	59.9	VESA	VGA (60Hz)
640 x 480	37.9	72.8	VESA	VGA (72Hz)
640 x 480	37.5	75.0	VESA	VGA (75Hz)
640 x 480	43.3	85.0	VESA	VGA (85Hz)
800 x 600	35.2	56.3	VESA	SVGA (56Hz)
800 x 600	37.9	60.3	VESA	SVGA (60Hz)
800 x 600	48.1	72.2	VESA	SVGA (72Hz)
800 x 600	46.9	75.0	VESA	SVGA (75Hz)
800 x 600	53.7	85.1	VESA	SVGA (85Hz)
832 x 624	49.7	74.5		Mac 16" mode
1024 x 768	48.4	60.0	VESA	XGA (60Hz)
1024 x 768	56.5	70.1	VESA	XGA (70Hz)
1024 x 768	60.0	75.0	VESA	XGA (75Hz)
1024 x 768	68.7	85.0	VESA	XGA (85Hz)
1152 x 864	67.5	75.0	VESA	1152 x 864 (75Hz)
1280 x 768	47.7	60.0	VESA	W-XGA (60Hz)
1280 x 800	49.7	60.0	VESA	1280 x 800 (60Hz)
1280 x 960	60.0	60.0	VESA	1280 x 960 (60Hz)
1280 x 1024	64.0	60.0	VESA	SXGA (60Hz)
1280 x 1024	80.0	75.0	VESA	SXGA (75Hz)
1440 x 900	55.9	59.9	VESA	WXGA+ (60Hz)

(continued on next page)

Example of computer signal

Resolution (H x V)	H. frequency (kHz)	V. frequency (Hz)	Rating	Signal mode
*1 1280 x 1024	91.1	85.0	VESA	SXGA (85Hz)
*2 1400 x 1050	65.2	60.0	VESA	SXGA+ (60Hz)
*3 1680 x 1050	65.3	60.0	VESA	WSXGA+ (60Hz)
*1 1600 x 1200	75.0	60.0	VESA	UXGA (60Hz)
*4 1920 x 1200	74.0	60.0	VESA	W-UXGA (60Hz) Reduced Blanking

*1) Supported except for HDMI™ input.

*2) Only for **CP-X9110**.

*3) Only for **CP-WX9210** and **CP-WU9410**.


*4) Only for **CP-WU9410**, but except for HDMI™ input.

NOTE • Be sure to check jack type, signal level, timing and resolution before connecting this projector to a computer.

- Some computers may have multiple display screen modes. Use of some of these modes will not be possible with this projector.
- Depending on the input signal, full-size display may not be possible in some cases. Refer to the number of display pixels above.
- Although the projector can display signals with a resolution up to UXGA (1600x1200) or up to W-UXGA (1920x1200) for **CP-WU9410**, the signal will be converted to the projector's panel resolution before being displayed. The best display performance will be achieved if the resolutions of the input signal and projector panel are identical.
- Automatic adjustment may not function correctly with some input signals.
- The image may not be displayed correctly when the input sync signal is a composite sync or a sync on G.
- The illustrations in this manual are for illustrative purposes. They may differ slightly from your projector.

Initial set signals

The following signals are used for the initial settings. The signal timing of some computer models may be different. In such case, adjust the items V POSITION and H POSITION in the IMAGE menu.




Resolution (H x V)	Horizontal signal timing (μs)				Vertical signal timing (lines)				Signal mode
	(A)	(B)	(C)	(D)	(a)	(b)	(c)	(d)	
720 x 400	2.0	3.0	20.3	1.0	3	42	400	1	TEXT
640 x 480	3.8	1.9	25.4	0.6	2	33	480	10	VGA (60Hz)
640 x 480	1.3	4.1	20.3	0.8	3	28	480	9	VGA (72Hz)
640 x 480	2.0	3.8	20.3	0.5	3	16	480	1	VGA (75Hz)
640 x 480	1.6	2.2	17.8	1.6	3	25	480	1	VGA (85Hz)
800 x 600	2.0	3.6	22.2	0.7	2	22	600	1	SVGA (56Hz)
800 x 600	3.2	2.2	20.0	1.0	4	23	600	1	SVGA (60Hz)
800 x 600	2.4	1.3	16.0	1.1	6	23	600	37	SVGA (72Hz)
800 x 600	1.6	3.2	16.2	0.3	3	21	600	1	SVGA (75Hz)
800 x 600	1.1	2.7	14.2	0.6	3	27	600	1	SVGA (85Hz)
832 x 624	1.1	3.9	14.5	0.6	3	39	624	1	Mac 16" mode
1024 x 768	2.1	2.5	15.8	0.4	6	29	768	3	XGA (60Hz)
1024 x 768	1.8	1.9	13.7	0.3	6	29	768	3	XGA (70Hz)
1024 x 768	1.2	2.2	13.0	0.2	3	28	768	1	XGA (75Hz)
1024 x 768	1.0	2.2	10.8	0.5	3	36	768	1	XGA (85Hz)
1152 x 864	1.2	2.4	10.7	0.6	3	32	864	1	1152 x 864 (75Hz)
1280 x 768	1.7	2.5	16.0	0.8	3	23	768	1	W-XGA (60Hz)
1280 x 800	1.6	2.4	15.3	0.8	3	24	800	1	1280 x 800 (60Hz)
1280 x 960	1.0	2.9	11.9	0.9	3	36	960	1	1280 x 960 (60Hz)
1280 x 1024	1.0	2.3	11.9	0.4	3	38	1024	1	SXGA (60Hz)
1280 x 1024	1.1	1.8	9.5	0.1	3	38	1024	1	SXGA (75Hz)
1280 x 1024	1.0	1.4	8.1	0.4	3	44	1024	1	SXGA (85Hz)
1400 x 1050	1.2	2.0	11.4	0.7	3	33	1050	1	SXGA+ (60Hz)
1440 x 900	1.4	2.2	13.5	0.8	6	25	900	3	WXGA+ (60Hz)
1680 x 1050	1.2	1.9	11.5	0.7	6	30	1050	3	WSXGA+ (60Hz)
1600 x 1200	1.2	1.9	9.9	0.4	3	46	1200	1	UXGA (60Hz)
1920 x 1200	0.208	0.519	12.47	0.312	6	26	1200	3	W-UXGA (60Hz) Reduced Blanking

Connection to the ports


NOTICE ▶ Use the cables with straight plugs, not L-shaped ones, as the input ports of the projector are recessed.

▶ Only the signal that is input from the **COMPUTER IN1** or **IN2** can be output from the **MONITOR OUT** port.



ⒶCOMPUTER IN1, ⒷMONITOR OUT

D-sub 15pin mini shrink jack




<Computer signal>

- Video signal: RGB separate, Analog, 0.7Vp-p, 75Ω terminated (positive)
- H/V. sync. signal: TTL level (positive/negative)
- Composite sync. signal: TTL level

<Component video signal>

- Video signal: Y with composite sync, Analog, 1.0±0.1Vp-p, 75Ω terminated
Cb/Pb, Analog, 0.7±0.1Vp-p, 75Ω terminated
Cr/Pr, Analog, 0.7±0.1Vp-p 75Ω terminated
- System: 480i@60, 480p@60, 576i@50, 720p@50/60, 1080i@50/60, 1080p@50/60

Pin	Signal	Pin	Signal
1	Video Red, Cr/Pr	9	(No connection)
2	Video Green, Y	10	Ground
3	Video Blue, Cb/Pb	11	(No connection)
4	(No connection)	12	Ⓐ: SDA (DDC data) Ⓑ: (No connection)
5	Ground	13	H. sync / Composite sync.
6	Ground Red, Ground Cr/Pr	14	V. sync.
7	Ground Green, Ground Y	15	Ⓐ: SCL (DDC clock) Ⓑ: (No connection)
8	Ground Blue, Ground Cb/Pb		



COMPUTER IN2 ③R/Cr/Pr, ④G/Y, ⑤B/Cb/Pb, ⑥H, ⑦V

BNC jack x5

<Computer signal>


- Video signal: RGB separate, Analog, 0.7Vp-p, 75Ω terminated (positive)
- H/V. sync. signal: TTL level (positive/negative)
- Composite sync. signal: TTL level

<Component video signal>


- Video signal: Y with composite sync, Analog, 1.0±0.1Vp-p, 75Ω terminated
- Cb/Pb, Analog, 0.7±0.1Vp-p, 75Ω terminated
- Cr/Pr, Analog, 0.7±0.1Vp-p 75Ω terminated
- System: 480i@60, 480p@60, 576i@50, 720p@50/60, 1080i@50/60, 1080p@50/60

⑧HDMI 1, ⑨HDMI 2

HDMI™ connector




Pin	Signal	Pin	Signal	Pin	Signal
1	T.M.D.S. Data2 +	8	T.M.D.S. Data0 Shield	15	SCL
2	T.M.D.S. Data2 Shield	9	T.M.D.S. Data0 -	16	SDA
3	T.M.D.S. Data2 -	10	T.M.D.S. Clock +	17	DDC/CEC Ground
4	T.M.D.S. Data1 +	11	T.M.D.S. Clock Shield	18	+5V Power
5	T.M.D.S. Data1 Shield	12	T.M.D.S. Clock -	19	Hot Plug Detect
6	T.M.D.S. Data1 -	13	CEC		
7	T.M.D.S. Data0 +	14	Reserved (N.C. on device)		



J DVI-D

DVI-D jack (digital to digital)




Pin	Signal	Pin	Signal	Pin	Signal
1	T.M.D.S. Data2 -	9	T.M.D.S. Data1 -	17	T.M.D.S. Data0 -
2	T.M.D.S. Data2 +	10	T.M.D.S. Data1 +	18	T.M.D.S. Data0 +
3	T.M.D.S. Data2/4 Shield	11	T.M.D.S. Data1/3 Shield	19	T.M.D.S. Data0/5 Shield
4	-	12	-	20	-
5	-	13	-	21	-
6	DDC Clock	14	+5V Power	22	T.M.D.S. Clock Shield
7	DDC Data	15	Ground (for +5V)	23	T.M.D.S. Clock +
8	-	16	Hot Plug Detect	24	T.M.D.S. Clock -

K VIDEO

BNC jack


- Composite video signal, Analog, 1.0±0.1Vp-p, 75Ω terminator
- System: NTSC, PAL, SECAM, PAL-M, PAL-N, NTSC4.43, PAL(60Hz)




Ⓛ CONTROL

D-sub 9pin plug

* About the details of RS-232C communication, please refer to the next section.




Pin	Signal	Pin	Signal	Pin	Signal
1	(No connection)	4	(No connection)	7	RTS
2	RD	5	Ground	8	CTS
3	TD	6	(No connection)	9	(No connection)



M HDBaseT


RJ-45 jack




Pin	Signal	Pin	Signal	Pin	Signal
1	HDBaseT0+	4	HDBaseT2+	7	HDBaseT3+
2	HDBaseT0-	5	HDBaseT2-	8	HDBaseT3-
3	HDBaseT1+	6	HDBaseT1-		

N LAN

RJ-45 jack




Pin	Signal	Pin	Signal	Pin	Signal
1	TX+	4	-	7	-
2	TX-	5	-	8	-
3	RX+	6	RX-		



④ WIRELESS PORT

Only for USB wireless adapter.



Pin	Signal
1	+5V
2	- Data
3	+ Data
4	Ground

REMOTE CONTROL ③IN, ④OUT

Ø3.5 stereo mini jack


RS-232C Communication

When the projector connects to the computer by RS-232C communication, the projector can be controlled with RS-232C commands from the computer.

For details of RS-232C commands, refer to RS-232C Communication / Network command table (📖 19).

Connection

1. Turn off the projector and the computer.
2. Connect the projector's **CONTROL** port and the computer's RS-232C port with a RS-232C cable (cross). Use the cable that fulfills the specification shown in figure.
3. Turn the computer on, and turn the projector on after the computer has started up.
4. Set the COMMUNICATION TYPE to OFF in the COMMUNICATION menu of the OPTION - SERVICE menu.



Communication settings

1. Protocol

19200bps, 8N1

2. Command format ("h" shows hexadecimal)

Byte Number	0	1	2	3	4	5	6	7	8	9	10	11	12
Command Action	Header							Data					
	Header code		Packet	Data size		CRC flag		Action		Type		Setting code	
	L	H		L	H	L	H	L	H	L	H	L	H
<SET>Change setting to desired value [(cL)(cH)] by [(bL)(bH)].	BEh	EFh	03h	06h	00h	(aL)	(aH)	01h	00h	(bL)	(bH)	(cL)	(cH)
<GET>Read projector internal setup value [(bL)(bH)] .						(aL)	(aH)	02h	00h	(bL)	(bH)	00h	00h
<INCREMENT> Increment setup value [(bL)(bH)] by 1.						(aL)	(aH)	04h	00h	(bL)	(bH)	00h	00h
<DECREMENT> Decrement setup value [(bL)(bH)] by 1.						(aL)	(aH)	05h	00h	(bL)	(bH)	00h	00h
<EXECUTE> Run a command [(bL)(bH)].						(aL)	(aH)	06h	00h	(bL)	(bH)	00h	00h

[Header code] [Packet] [Data size]

Set [BEh, EFh, 03h, 06h, 00h] to byte number 0 to 4.

[CRC flag]

For byte number 5 and 6, refer to RS-232C Communication / Network command table (📖 19).

[Action]

Set functional code to byte number 7 and 8.

<SET> = [01h, 00h], <GET> = [02h, 00h], <INCREMENT> = [04h, 00h]

<DECREMENT> = [05h, 00h], <EXECUTE> = [06h, 00h]

Refer to the Communication command table (📖 above).

[Type] [Setting code]

For byte number 9 to 12, refer to RS-232C Communication / Network command table (📖 19).

3. Response code / Error code ("h" shows hexadecimal)

(1) ACK reply: 06h

When the projector receives the Set, Increment, Decrement or Execute command correctly, the projector changes the setting data for the specified item by [Type], and it returns the code.

(2) NAK reply: 15h

When the projector cannot understand the received command, the projector returns the error code.

In such a case, check the sending code and send the same command again.

(3) Error reply: 1Ch + 0000h

When the projector cannot execute the received command for any reasons, the projector returns the error code.

In such a case, check the sending code and the setting status of the projector.

(4) Data reply: 1Dh + xxxxh

When the projector receives the GET command correctly, the projector returns the response code and 2 bytes of data.

NOTE • For connecting the projector to your devices, please read the manual for each device, and connect them correctly with suitable cables.

- Operation cannot be guaranteed when the projector receives an undefined command or data.

- Provide an interval of at least 40ms between the response code and any other code.

- The projector outputs test data when the power supply is switched ON, and when the lamp is lit. Ignore this data.

- Commands are not accepted during warm-up.

- When the data length is greater than indicated by the data length code, the projector ignores the excess data code. Conversely when the data length is shorter than indicated by the data length code, the projector returns the error code to the computer.

Command Control via the Network


When the projector connects to the network, the projector can be controlled with RS-232C commands from the computer with web browser.

For details of RS-232C commands, refer to RS-232C Communication / Network command table (📖 19).

NOTE • If data is transferred via wireless and wired LAN at the same time, the projector may not be able to process the data correctly.

Connection

1. Turn off the projector and the computer.
2. If you use wired LAN, connect the projector's **LAN** or **HDBaseT™** port to the computer's LAN or HDBaseT port with a LAN cable. Use the cable that fulfills the specification shown in figure. If you use wireless LAN, insert the USB wireless adapter into the **WIRELESS** port of the projector.
3. Turn the computer on, and turn the projector on after the computer has started up.



Communication Port

The following two ports are assigned for the command control.

TCP #23

TCP #9715

Configure the following items from a web browser when command control is used.

Port Settings		
Network Control Port1 (Port: 23)	Port open	Click the [Enable] check box to open [Network Control Port1 (Port: 23)] to use TCP #23. Default setting is "Enable".
	Authentication	Click the [Enable] check box for the [Authentication] setting when authentication is required. Default setting is "Disable".
Network Control Port2 (Port: 9715)	Port open	Click the [Enable] check box to open [Network Control Port2 (Port: 9715)] to use TCP #9715. Default setting is "Enable".
	Authentication	Click the [Enable] check box for the [Authentication] setting when authentication is required. Default setting is "Enable".

When the authentication setting is enabled, the following settings are required.

Security Settings		
Network Control	Authentication Password	Enter the desired authentication password. Confirm this setting will be the same for [Network Control Port1 (Port: 23)] and [Network Control Port2 (Port: 9715)] . Default setting is blank.
	Re-enter Authentication Password	

Command control settings

[TCP #23]

1. Command format

Same as RS-232C communication, refer to RS-232C Communication command format.

2. Response code / Error code ("h" shows hexadecimal)

Four of the response / error code used for TCP#23 are the same as RS-232C Communication (1)~(4). One authentication error reply (5) is added.

(1) **ACK reply : 06h**

Refer to RS-232C communication (📖 12).

(2) **NAK reply : 15h**

Refer to RS-232C communication (📖 12).

(3) **Error reply : 1Ch + 0000h**

Refer to RS-232C communication (📖 12).

(4) **Data reply : 1Dh + xxxxh**

Refer to RS-232C communication (📖 12).

(5) **Authentication error reply : 1Fh + 0400h**

When authentication error occurs, the projector returns the error code.

[TCP #9715]

1. Command format

The commands that some datum are added to the head and the end of the ones of TCP#9715 are used.

Header	Data length	RS-232C command	Check sum	Connection ID
0x02	0x0D	13 bytes	1 byte	1 byte

[Header]

02, Fixed

[Data Length]

RS-232C commands byte length (0x0D, Fixed)

[RS-232C commands]

Refer to RS-232C Communication command format (📖 11).

[Check Sum]

This is the value to make zero on the addition of the lower 8 bits from the header to the checksum.

[Connection ID]

Random value from 0 to 255 (This value is attached to the reply data).

NOTE • Operation cannot be guaranteed when the projector receives an undefined command or data.

- Provide an interval of at least 40ms between the response code and any other code.
- Commands are not accepted during warm-up.

2. Response code / Error code ("h" shows hexadecimal)

The connection ID is attached for the TCP#23's response / error codes are used. The connection ID is the same as the sending command format.

- (1) **ACK reply:** **06h + xxh** (xxh : connection ID)
- (2) **NAK reply:** **15h + xxh**
- (3) **Error reply:** **1Ch + 0000h + xxh**
- (4) **Data reply:** **1Dh + xxxxh + xxh**
- (5) **Authentication error reply:** **1Fh + 0400h + xxh**
- (6) **Projector busy reply:** **1Fh + xxxxh + xxh**

When the projector is too busy to receive the command, the projector returns the error code.

In such a case, check the sending code and send the same command again.

Automatic Connection Break

The TCP connection will be automatically disconnected after there is no communication for 30 seconds after being established.

Authentication

The projector does not accept commands without authentication success when authentication is enabled. The projector uses a challenge response type authentication with an MD5 (Message Digest 5) algorithm.

When the projector is connected to a LAN, a random 8 bytes will be returned if authentication is enabled. Bind this received 8 bytes and the authentication password, and digest the data with the MD5 algorithm, and add it in front of the commands to send.

Following is a sample of authentication process.

Authentication password: **password** (example)

Random 8 bytes: **a572f60c** (example)

- 1) Select a projector and receive the random 8 bytes from the projector.
→ "a572f60c"
- 2) Bind the random 8 bytes and the authentication password.
→ "a572f60cpassword"
- 3) Digest this bound with MD5 algorithm.
→ "e3d97429adffa11bce1f7275813d4bde"
- 4) Add this code in front of the commands and send the data.
→ "e3d97429adffa11bce1f7275813d4bde" + [command].
- 5) When the sent data is correct, the command will be performed and the reply data will be returned. Otherwise, an authentication error will be returned.

NOTE • As for the transmission of the second or subsequent commands, the authentication data can be omitted for the same connection.

Network Bridge Communication


This projector is equipped with NETWORK BRIDGE function.

When the projector connects to the computer by wired or wireless LAN communication, an external device that is connected with this projector by RS-232C communication can be controlled from the computer as a network terminal. For details, see the **7. Network Bridge** function in the **Network Guide**.

NOTE • If data is transferred via wireless and wired LAN at the same time, the projector may not be able to process the data correctly.

Connection

1. If you use wired LAN, connect the computer's LAN or HDBaseT™ port and the projector's **LAN** or HDBaseT port with a LAN cable. Use the cable that fulfills the specification shown in figure. If you use wireless LAN, insert the USB wireless adapter into the projector's **WIRELESS** port.
2. Connect the projector's **CONTROL** port and the RS-232C port of the devices that you want to control with a RS-232C cable.
3. Turn the computer on, and turn the projector on after the computer has started up.
4. Set the COMMUNICATION TYPE to NETWORK BRIDGE in the OPTION - SERVICE menu.



Communication settings

For communication setting, use the COMMUNICATION menu in the OPTION - SERVICE menu.

Item	Condition
BAUD RATE	4800bps / 9600bps / 19200bps / 38400bps
Data length	8 bit (fixed)
PARITY	NONE/ODD/EVEN
Start bit	1 bit (fixed)
Stop bit	1 bit (fixed)
Transmission method	HALF-DUPLEX/FULL-DUPLEX

NOTE • For connecting the projector to your devices, please read the manual for each devices, and connect them correctly with suitable cables.
 • Turn off the power and unplug both the projector and other devices before connecting them.
 • For details of Transmission method, refer to **7.4 Transmission method** in the **Network Guide**.

RS-232C Communication / Network command table

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
Power	Set	Turn off	BE EF 03 06 00	2A D3	01 00	00 60
		Turn on	BE EF 03 06 00	BA D2	01 00	00 60
	Get	BE EF 03 06 00	19 D3	02 00	00 60	00 00
		[Example return] 00 00 01 00 02 00 [Off] [On] [Cool down]				
Input Source	Set	COMPUTER IN1	BE EF 03 06 00	FE D2	01 00	00 20
		COMPUTER IN2	BE EF 03 06 00	3E D0	01 00	00 20
		LAN	BE EF 03 06 00	CE D5	01 00	00 20
		HDMI 1	BE EF 03 06 00	0E D2	01 00	00 20
		HDMI 2	BE EF 03 06 00	6E D6	01 00	00 20
		DVI-D	BE EF 03 06 00	AE D4	01 00	00 20
		HDBaseT	BE EF 03 06 00	AE DE	01 00	00 20
		VIDEO	BE EF 03 06 00	6E D3	01 00	00 20
Error Status	Get	BE EF 03 06 00	CD D2	02 00	00 20	00 00
		BE EF 03 06 00	D9 D8	02 00	20 60	00 00
		[Example return] 00 00 01 00 02 00 03 00 [Normal] [Cover error] [Fan error] [Lamp error] 04 00 05 00 07 00 08 00 [Temp error] [Air flow error] [Cold error] [Filter error] 0F 00 10 00 13 00 23 00 [Shutter error][Lens Shift error][Lamp-1 warning][Lamp-2 warning] 41 00 [Humidity error] 42 00, 43 00, 44 00, 50 00, 51 00, 54 00, 55 00, 56 00 [Other error] 52 00 53 00 [Color Wheel error] [Active Iris error]				
		BE EF 03 06 00	6A 93	04 00	00 24	00 00
FOCUS	Increment	BE EF 03 06 00	BB 92	05 00	00 24	00 00
	Decrement	BE EF 03 06 00	BB 92	05 00	00 24	00 00
ZOOM	Increment	BE EF 03 06 00	96 92	04 00	01 24	00 00
	Decrement	BE EF 03 06 00	47 93	05 00	01 24	00 00
LENS SHIFT - V	Increment	BE EF 03 06 00	D2 92	04 00	02 24	00 00
	Decrement	BE EF 03 06 00	03 93	05 00	02 24	00 00
LENS SHIFT - H	Increment	BE EF 03 06 00	2E 93	04 00	03 24	00 00
	Decrement	BE EF 03 06 00	FF 92	05 00	03 24	00 00
LENS SHIFT CENTERING	Execute	BE EF 03 06 00	B8 93	06 00	04 24	00 00
LENS MEMORY INDEX	Set	1	BE EF 03 06 00	4B 92	01 00	07 24
		2	BE EF 03 06 00	DB 93	01 00	07 24
		3	BE EF 03 06 00	2B 93	01 00	07 24
	Get	BE EF 03 06 00	78 92	02 00	07 24	00 00
LENS MEMORY LOAD	Execute	BE EF 03 06 00	E8 90	06 00	08 24	00 00
LENS MEMORY SAVE	Execute	BE EF 03 06 00	14 91	06 00	09 24	00 00
LENS MEMORY CLEAR	Execute	BE EF 03 06 00	50 91	06 00	0A 24	00 00

(continued on next page)

Names	Operation Type	Header			CRC	Command Data			
						Action	Type	Setting code	
LENS MEMORY LENS SHIFT - V	Get	BE EF	03	06 00	A0 91	02 00	0D 24	00 00	
LENS MEMORY LENS SHIFT - H	Get	BE EF	03	06 00	E4 91	02 00	0E 24	00 00	
LENS MEMORY LENS TYPE	Get	BE EF	03	06 00	18 90	02 00	0F 24	00 00	
MAGNIFY	Get	BE EF	03	06 00	7C D2	02 00	07 30	00 00	
	Increment	BE EF	03	06 00	1A D2	04 00	07 30	00 00	
	Decrement	BE EF	03	06 00	CB D3	05 00	07 30	00 00	
MAGNIFY Position H	Get	BE EF	03	06 00	C8 D7	02 00	10 30	00 00	
	Increment	BE EF	03	06 00	AE D7	04 00	10 30	00 00	
	Decrement	BE EF	03	06 00	7F D6	05 00	10 30	00 00	
MAGNIFY Position V	Get	BE EF	03	06 00	34 D6	02 00	11 30	00 00	
	Increment	BE EF	03	06 00	52 D6	04 00	11 30	00 00	
	Decrement	BE EF	03	06 00	83 D7	05 00	11 30	00 00	
FREEZE	Set	NORMAL	BE EF	03	06 00	83 D2	01 00	02 30	00 00
		FREEZE	BE EF	03	06 00	13 D3	01 00	02 30	01 00
		Get	BE EF	03	06 00	B0 D2	02 00	02 30	00 00
SHUTTER	Set	OFF	BE EF	03	06 00	F3 93	01 00	05 24	00 00
		ON	BE EF	03	06 00	63 92	01 00	05 24	01 00
		Get	BE EF	03	06 00	C0 93	02 00	05 24	00 00
PbyP/PinP	Set	OFF	BE EF	03	06 00	3E 26	01 00	10 23	00 00
		PbyP	BE EF	03	06 00	AE 27	01 00	10 23	01 00
		PinP	BE EF	03	06 00	5E 27	01 00	10 23	02 00
		Get	BE EF	03	06 00	0D 26	02 00	10 23	00 00
PbyP MAIN SIZE	Set	SMALL	BE EF	03	06 00	F2 07	01 00	11 23	7F 00
		MIDDLE	BE EF	03	06 00	02 46	01 00	11 23	80 00
		LARGE	BE EF	03	06 00	92 47	01 00	11 23	81 00
		Get	BE EF	03	06 00	F1 27	02 00	11 23	00 00
PbyP RIGHT SOURCE	Set	COMPUTER 1	BE EF	03	06 00	86 27	01 00	12 23	00 00
		COMPUTER 2	BE EF	03	06 00	46 25	01 00	12 23	04 00
		HDMI 1	BE EF	03	06 00	76 27	01 00	12 23	03 00
		HDMI 2	BE EF	03	06 00	16 23	01 00	12 23	0D 00
		DVI-D	BE EF	03	06 00	D6 21	01 00	12 23	09 00
		HDBase-T	BE EF	03	06 00	D6 2B	01 00	12 23	11 00
	VIDEO	BE EF	03	06 00	16 26	01 00	12 23	01 00	
	Get	BE EF	03	06 00	B5 27	02 00	12 23	00 00	
PbyP MAIN AREA	Set	LEFT	BE EF	03	06 00	7A 26	01 00	13 23	00 00
		RIGHT	BE EF	03	06 00	EA 27	01 00	13 23	01 00
		Get	BE EF	03	06 00	49 26	02 00	13 23	00 00
PbyP LEFT SOURCE	Set	COMPUTER 1	BE EF	03	06 00	F2 26	01 00	15 23	00 00
		COMPUTER 2	BE EF	03	06 00	32 24	01 00	15 23	04 00
		HDMI 1	BE EF	03	06 00	02 26	01 00	15 23	03 00
		HDMI 2	BE EF	03	06 00	62 22	01 00	15 23	0D 00
		DVI-D	BE EF	03	06 00	A2 20	01 00	15 23	09 00
		HDBase-T	BE EF	03	06 00	A2 2A	01 00	15 23	11 00
	VIDEO	BE EF	03	06 00	62 27	01 00	15 23	01 00	
	Get	BE EF	03	06 00	C1 26	02 00	15 23	00 00	

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
PinP POSITION	Set	TOP LEFT	BE EF 03 06 00	02 23	01 00	00 00
		TOP RIGHT	BE EF 03 06 00	92 22	01 00	01 00
		BOTTOM LEFT	BE EF 03 06 00	62 22	01 00	02 00
		BOTTOM RIGHT	BE EF 03 06 00	F2 23	01 00	03 00
	Get		BE EF 03 06 00	31 23	02 00	01 23
PinP MAIN AREA	Set	PRIMARY	BE EF 03 06 00	32 22	01 00	05 23
		SECONDARY	BE EF 03 06 00	A2 23	01 00	05 23
	Get		BE EF 03 06 00	01 22	02 00	05 23
PinP PRIMARY SOURCE	Set	COMPUTER IN 1	BE EF 03 06 00	CE 23	01 00	04 23
		COMPUTER IN 2	BE EF 03 06 00	0E 21	01 00	04 23
		HDMI 1	BE EF 03 06 00	3E 23	01 00	04 23
		HDMI 2	BE EF 03 06 00	5E 27	01 00	04 23
		DVI-D	BE EF 03 06 00	9E 25	01 00	04 23
		HDBase-T	BE EF 03 06 00	9E 2F	01 00	04 23
	Get	VIDEO	BE EF 03 06 00	5E 22	01 00	04 23
PinP SECONDARY SOURCE	Set	COMPUTER IN 1	BE EF 03 06 00	FD 23	02 00	04 23
		COMPUTER IN 2	BE EF 03 06 00	46 23	01 00	02 23
		HDMI 1	BE EF 03 06 00	86 21	01 00	02 23
		HDMI 2	BE EF 03 06 00	B6 23	01 00	02 23
		DVI-D	BE EF 03 06 00	D6 27	01 00	02 23
		HDBase-T	BE EF 03 06 00	16 25	01 00	02 23
	Get	VIDEO	BE EF 03 06 00	16 2F	01 00	02 23
PbyP SWAP	Execute		BE EF 03 06 00	D6 22	01 00	02 23
PbyP / PinP FRAME LOCK	Set	LEFT / PRIMARY	BE EF 03 06 00	75 23	02 00	02 23
		RIGHT / SECONDARY	BE EF 03 06 00	4A 27	01 00	17 23
	Get		BE EF 03 06 00	DA 26	01 00	17 23
PICTURE MODE	Set	STANDARD	BE EF 03 06 00	79 27	02 00	17 23
		NATURAL	BE EF 03 06 00	83 F5	01 00	BA 30
		CINEMA	BE EF 03 06 00	23 F6	01 00	BA 30
		CINEMA	BE EF 03 06 00	B3 F7	01 00	BA 30
		DYNAMIC	BE EF 03 06 00	E3 F4	01 00	BA 30
		BOARD(BLACK)	BE EF 03 06 00	E3 EF	01 00	BA 30
		BOARD(GREEN)	BE EF 03 06 00	73 EE	01 00	BA 30
		WHITEBOARD	BE EF 03 06 00	73 EE	01 00	BA 30
		DAYTIME	BE EF 03 06 00	83 EE	01 00	BA 30
		DICOM SIM.	BE EF 03 06 00	E3 C7	01 00	BA 30
		USER-1	BE EF 03 06 00	73 C6	01 00	BA 30
BRIGHTNESS	Get	USER-2	BE EF 03 06 00	E3 FB	01 00	BA 30
		USER-3	BE EF 03 06 00	73 FA	01 00	BA 30
	Get		BE EF 03 06 00	83 FA	01 00	BA 30
BRIGHTNESS Reset	Execute		BE EF 03 06 00	10 F6	02 00	BA 30
			BE EF 03 06 00	89 D2	02 00	03 20
			BE EF 03 06 00	EF D2	04 00	03 20
BRIGHTNESS	Increment		BE EF 03 06 00	3E D3	05 00	03 20
			BE EF 03 06 00	58 D3	06 00	00 70
			BE EF 03 06 00	58 D3	06 00	00 00

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
CONTRAST	Get		BE EF	03	06 00	FD D3	02 00	04 20	00 00
	Increment		BE EF	03	06 00	9B D3	04 00	04 20	00 00
	Decrement		BE EF	03	06 00	4A D2	05 00	04 20	00 00
CONTRAST Reset	Execute		BE EF	03	06 00	A4 D2	06 00	01 70	00 00
GAMMA	Set	1 DEFAULT	BE EF	03	06 00	07 E9	01 00	A1 30	20 00
		1 CUSTOM	BE EF	03	06 00	07 FD	01 00	A1 30	10 00
		2 DEFAULT	BE EF	03	06 00	97 E8	01 00	A1 30	21 00
		2 CUSTOM	BE EF	03	06 00	97 FC	01 00	A1 30	11 00
		3 DEFAULT	BE EF	03	06 00	67 E8	01 00	A1 30	22 00
		3 CUSTOM	BE EF	03	06 00	67 FC	01 00	A1 30	12 00
		4 DEFAULT	BE EF	03	06 00	F7 E9	01 00	A1 30	23 00
		4 CUSTOM	BE EF	03	06 00	F7 FD	01 00	A1 30	13 00
		5 DEFAULT	BE EF	03	06 00	C7 EB	01 00	A1 30	24 00
		5 CUSTOM	BE EF	03	06 00	C7 FF	01 00	A1 30	14 00
		6 DEFAULT	BE EF	03	06 00	57 EA	01 00	A1 30	25 00
		6 CUSTOM	BE EF	03	06 00	57 FE	01 00	A1 30	15 00
	7 DEFAULT	BE EF	03	06 00	A7 EA	01 00	A1 30	26 00	
	7 CUSTOM	BE EF	03	06 00	A7 FE	01 00	A1 30	16 00	
	8 DEFAULT	BE EF	03	06 00	37 EB	01 00	A1 30	27 00	
	8 CUSTOM	BE EF	03	06 00	37 FF	01 00	A1 30	17 00	
Get		BE EF	03	06 00	F4 F0	02 00	A1 30	00 00	
User GAMMA Pattern	Set	Off	BE EF	03	06 00	FB FA	01 00	80 30	00 00
		9 steps gray scale	BE EF	03	06 00	6B FB	01 00	80 30	01 00
		15 steps gray scale	BE EF	03	06 00	9B FB	01 00	80 30	02 00
		Ramp	BE EF	03	06 00	0B FA	01 00	80 30	03 00
	Get		BE EF	03	06 00	C8 FA	02 00	80 30	00 00

Names	Operation Type	Header			CRC	Command Data		
						Action	Type	Setting code
User GAMMA Point 1	Get	BE EF	03	06 00	08 FE	02 00	90 30	00 00
	Increment	BE EF	03	06 00	6E FE	04 00	90 30	00 00
	Decrement	BE EF	03	06 00	BF FF	05 00	90 30	00 00
User GAMMA Point 1 Reset	Execute	BE EF	03	06 00	58 C2	06 00	50 70	00 00
User GAMMA Point 2	Get	BE EF	03	06 00	F4 FF	02 00	91 30	00 00
	Increment	BE EF	03	06 00	92 FF	04 00	91 30	00 00
	Decrement	BE EF	03	06 00	43 FE	05 00	91 30	00 00
User GAMMA Point 2 Reset	Execute	BE EF	03	06 00	A4 C3	06 00	51 70	00 00
User GAMMA Point 3	Get	BE EF	03	06 00	B0 FF	02 00	92 30	00 00
	Increment	BE EF	03	06 00	D6 FF	04 00	92 30	00 00
	Decrement	BE EF	03	06 00	07 FE	05 00	92 30	00 00
User GAMMA Point 3 Reset	Execute	BE EF	03	06 00	E0 C3	06 00	52 70	00 00
User GAMMA Point 4	Get	BE EF	03	06 00	4C FE	02 00	93 30	00 00
	Increment	BE EF	03	06 00	2A FE	04 00	93 30	00 00
	Decrement	BE EF	03	06 00	FB FF	05 00	93 30	00 00
User GAMMA Point 4 Reset	Execute	BE EF	03	06 00	1C C2	06 00	53 70	00 00
User GAMMA Point 5	Get	BE EF	03	06 00	38 FF	02 00	94 30	00 00
	Increment	BE EF	03	06 00	5E FF	04 00	94 30	00 00
	Decrement	BE EF	03	06 00	8F FE	05 00	94 30	00 00
User GAMMA Point 5 Reset	Execute	BE EF	03	06 00	68 C3	06 00	54 70	00 00
User GAMMA Point 6	Get	BE EF	03	06 00	C4 FE	02 00	95 30	00 00
	Increment	BE EF	03	06 00	A2 FE	04 00	95 30	00 00
	Decrement	BE EF	03	06 00	73 FF	05 00	95 30	00 00
User GAMMA Point 6 Reset	Execute	BE EF	03	06 00	94 C2	06 00	55 70	00 00
User GAMMA Point 7	Get	BE EF	03	06 00	80 FE	02 00	96 30	00 00
	Increment	BE EF	03	06 00	E6 FE	04 00	96 30	00 00
	Decrement	BE EF	03	06 00	37 FF	05 00	96 30	00 00
User GAMMA Point 7 Reset	Execute	BE EF	03	06 00	D0 C2	06 00	56 70	00 00
User GAMMA Point 8	Get	BE EF	03	06 00	7C FF	02 00	97 30	00 00
	Increment	BE EF	03	06 00	1A FF	04 00	97 30	00 00
	Decrement	BE EF	03	06 00	CB FE	05 00	97 30	00 00
User GAMMA Point 8 Reset	Execute	BE EF	03	06 00	2C C3	06 00	57 70	00 00

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
COLOR TEMP	Set	1 HIGH	BE EF 03 06 00	0B F5	01 00	B0 30 03 00
		1 CUSTOM	BE EF 03 06 00	CB F8	01 00	B0 30 13 00
		2 MID-1	BE EF 03 06 00	9B F4	01 00	B0 30 02 00
		2 CUSTOM	BE EF 03 06 00	5B F9	01 00	B0 30 12 00
		3 MID-2	BE EF 03 06 00	3B F7	01 00	B0 30 04 00
		3 CUSTOM	BE EF 03 06 00	FB FA	01 00	B0 30 14 00
		4 LOW	BE EF 03 06 00	6B F4	01 00	B0 30 01 00
		4 CUSTOM	BE EF 03 06 00	AB F9	01 00	B0 30 11 00
		5 HI-BRIGHT-1	BE EF 03 06 00	3B F2	01 00	B0 30 08 00
		5 CUSTOM	BE EF 03 06 00	FB FF	01 00	B0 30 18 00
		6 HI-BRIGHT-2	BE EF 03 06 00	AB F3	01 00	B0 30 09 00
		6 CUSTOM	BE EF 03 06 00	6B FE	01 00	B0 30 19 00
		7 HI-BRIGHT-3	BE EF 03 06 00	5B F3	01 00	B0 30 0A 00
		7 CUSTOM	BE EF 03 06 00	9B FE	01 00	B0 30 1A 00
COLOR TEMP GAIN R	Get	BE EF 03 06 00	C8 F5	02 00	B0 30	00 00
	Get	BE EF 03 06 00	34 F4	02 00	B1 30	00 00
	Increment	BE EF 03 06 00	52 F4	04 00	B1 30	00 00
	Decrement	BE EF 03 06 00	83 F5	05 00	B1 30	00 00
COLOR TEMP GAIN R Reset	Execute	BE EF 03 06 00	10 C6	06 00	46 70	00 00
COLOR TEMP GAIN G	Get	BE EF 03 06 00	70 F4	02 00	B2 30	00 00
	Increment	BE EF 03 06 00	16 F4	04 00	B2 30	00 00
	Decrement	BE EF 03 06 00	C7 F5	05 00	B2 30	00 00
COLOR TEMP GAIN G Reset	Execute	BE EF 03 06 00	EC C7	06 00	47 70	00 00
COLOR TEMP GAIN B	Get	BE EF 03 06 00	8C F5	02 00	B3 30	00 00
	Increment	BE EF 03 06 00	EA F5	04 00	B3 30	00 00
	Decrement	BE EF 03 06 00	3B F4	05 00	B3 30	00 00
COLOR TEMP GAIN B Reset	Execute	BE EF 03 06 00	F8 C4	06 00	48 70	00 00
COLOR TEMP OFFSET R	Get	BE EF 03 06 00	04 F5	02 00	B5 30	00 00
	Increment	BE EF 03 06 00	62 F5	04 00	B5 30	00 00
	Decrement	BE EF 03 06 00	B3 F4	05 00	B5 30	00 00
COLOR TEMP OFFSET R Reset	Execute	BE EF 03 06 00	40 C5	06 00	4A 70	00 00
COLOR TEMP OFFSET G	Get	BE EF 03 06 00	40 F5	02 00	B6 30	00 00
	Increment	BE EF 03 06 00	26 F5	04 00	B6 30	00 00
	Decrement	BE EF 03 06 00	F7 F4	05 00	B6 30	00 00
COLOR TEMP OFFSET G Reset	Execute	BE EF 03 06 00	BC C4	06 00	4B 70	00 00
COLOR TEMP OFFSET B	Get	BE EF 03 06 00	BC F4	02 00	B7 30	00 00
	Increment	BE EF 03 06 00	DA F4	04 00	B7 30	00 00
	Decrement	BE EF 03 06 00	0B F5	05 00	B7 30	00 00
COLOR TEMP OFFSET B Reset	Execute	BE EF 03 06 00	C8 C5	06 00	4C 70	00 00
COLOR	Get	BE EF 03 06 00	B5 72	02 00	02 22	00 00
	Increment	BE EF 03 06 00	D3 72	04 00	02 22	00 00
	Decrement	BE EF 03 06 00	02 73	05 00	02 22	00 00

Names	Operation Type	Header			CRC	Command Data		
						Action	Type	Setting code
COLOR Reset	Execute	BE EF	03	06 00	80 D0	06 00	0A 70	00 00
TINT	Get	BE EF	03	06 00	49 73	02 00	03 22	00 00
	Increment	BE EF	03	06 00	2F 73	04 00	03 22	00 00
	Decrement	BE EF	03	06 00	FE 72	05 00	03 22	00 00
TINT Reset	Execute	BE EF	03	06 00	7C D1	06 00	0B 70	00 00
SHARPNESS	Get	BE EF	03	06 00	F1 72	02 00	01 22	00 00
	Increment	BE EF	03	06 00	97 72	04 00	01 22	00 00
	Decrement	BE EF	03	06 00	46 73	05 00	01 22	00 00
SHARPNESS Reset	Execute	BE EF	03	06 00	C4 D0	06 00	09 70	00 00
ACCENTUALIZER	Get	BE EF	03	06 00	5D 70	02 00	0C 22	00 00
	Increment	BE EF	03	06 00	3B 70	04 00	0C 22	00 00
	Decrement	BE EF	03	06 00	EA 71	05 00	0C 22	00 00
ACCENTUALIZER Reset	Execute	BE EF	03	06 00	C8 D8	06 00	2C 70	00 00
HDCR	Get	BE EF	03	06 00	A1 71	02 00	0D 22	00 00
	Increment	BE EF	03	06 00	C7 71	04 00	0D 22	00 00
	Decrement	BE EF	03	06 00	16 70	05 00	0D 22	00 00
HDCR Reset	Execute	BE EF	03	06 00	34 DA	06 00	2D 70	00 00
COLOR WHEEL	Set	BRIGHT	BE EF	03	06 00	FB C9	01 00	70 30
		RICH COLOR	BE EF	03	06 00	6B C8	01 00	70 30
	Get	BE EF	03	06 00	C8 C9	02 00	70 30	00 00
ACTIVE IRIS	Set	OFF	BE EF	03	06 00	0B 22	01 00	04 33
		THEATER	BE EF	03	06 00	CB 2F	01 00	04 33
		PRESENTATION	BE EF	03	06 00	5B 2E	01 00	04 33
	Get	BE EF	03	06 00	38 22	02 00	04 33	00 00
MY MEMORY Load	Set	1	BE EF	03	06 00	0E D7	01 00	14 20
		2	BE EF	03	06 00	9E D6	01 00	14 20
		3	BE EF	03	06 00	6E D6	01 00	14 20
		4	BE EF	03	06 00	FE D7	01 00	14 20
MY MEMORY Save	Set	1	BE EF	03	06 00	F2 D6	01 00	15 20
		2	BE EF	03	06 00	62 D7	01 00	15 20
		3	BE EF	03	06 00	92 D7	01 00	15 20
		4	BE EF	03	06 00	02 D6	01 00	15 20
ASPECT	Set	NORMAL	BE EF	03	06 00	5E DD	01 00	08 20
		4:3	BE EF	03	06 00	9E D0	01 00	08 20
		16:9	BE EF	03	06 00	0E D1	01 00	08 20
		16:10	BE EF	03	06 00	3E D6	01 00	08 20
		14:9	BE EF	03	06 00	CE D6	01 00	08 20
		NATIVE*	BE EF	03	06 00	5E D7	01 00	08 20
OVER SCAN	Get	BE EF	03	06 00	AD D0	02 00	08 20	00 00
	Increment	BE EF	03	06 00	91 70	02 00	09 22	00 00
	Decrement	BE EF	03	06 00	F7 70	04 00	09 22	00 00
OVER SCAN Reset	Execute	BE EF	03	06 00	26 71	05 00	09 22	00 00
OVER SCAN Reset	Execute	BE EF	03	06 00	EC D9	06 00	27 70	00 00

*) Supported except for **CP-X9110**.

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
V POSITION	Get		BE EF	03	06 00	0D 83	02 00	00 21	00 00
	Increment		BE EF	03	06 00	6B 83	04 00	00 21	00 00
	Decrement		BE EF	03	06 00	BA 82	05 00	00 21	00 00
V POSITION Reset	Execute		BE EF	03	06 00	E0 D2	06 00	02 70	00 00
H POSITION	Get		BE EF	03	06 00	F1 82	02 00	01 21	00 00
	Increment		BE EF	03	06 00	97 82	04 00	01 21	00 00
	Decrement		BE EF	03	06 00	46 83	05 00	01 21	00 00
H POSITION Reset	Execute		BE EF	03	06 00	1C D3	06 00	03 70	00 00
H PHASE	Get		BE EF	03	06 00	49 83	02 00	03 21	00 00
	Increment		BE EF	03	06 00	2F 83	04 00	03 21	00 00
	Decrement		BE EF	03	06 00	FE 82	05 00	03 21	00 00
H SIZE	Get		BE EF	03	06 00	B5 82	02 00	02 21	00 00
	Increment		BE EF	03	06 00	D3 82	04 00	02 21	00 00
	Decrement		BE EF	03	06 00	02 83	05 00	02 21	00 00
H SIZE Reset	Execute		BE EF	03	06 00	68 D2	06 00	04 70	00 00
AUTO ADJUST EXECUTE	Execute		BE EF	03	06 00	91 D0	06 00	0A 20	00 00
PROGRESSIVE	Set	OFF	BE EF	03	06 00	4A 72	01 00	07 22	00 00
		TV	BE EF	03	06 00	DA 73	01 00	07 22	01 00
		FILM	BE EF	03	06 00	2A 73	01 00	07 22	02 00
	Get		BE EF	03	06 00	79 72	02 00	07 22	00 00
VIDEO NR	Set	LOW	BE EF	03	06 00	26 72	01 00	06 22	01 00
		MID	BE EF	03	06 00	D6 72	01 00	06 22	02 00
		HIGH	BE EF	03	06 00	46 73	01 00	06 22	03 00
	Get		BE EF	03	06 00	85 73	02 00	06 22	00 00
COLOR SPACE	Set	AUTO	BE EF	03	06 00	0E 72	01 00	04 22	00 00
		RGB	BE EF	03	06 00	9E 73	01 00	04 22	01 00
		SMPTE240	BE EF	03	06 00	6E 73	01 00	04 22	02 00
		REC709	BE EF	03	06 00	FE 72	01 00	04 22	03 00
		REC601	BE EF	03	06 00	CE 70	01 00	04 22	04 00
	Get		BE EF	03	06 00	3D 72	02 00	04 22	00 00
C-VIDEO FORMAT	Set	AUTO	BE EF	03	06 00	A2 70	01 00	11 22	0A 00
		NTSC	BE EF	03	06 00	C2 74	01 00	11 22	04 00
		PAL	BE EF	03	06 00	52 75	01 00	11 22	05 00
		SECAM	BE EF	03	06 00	52 70	01 00	11 22	09 00
		NTSC4.43	BE EF	03	06 00	62 77	01 00	11 22	02 00
		M-PAL	BE EF	03	06 00	C2 71	01 00	11 22	08 00
	N-PAL	BE EF	03	06 00	32 74	01 00	11 22	07 00	
Get		BE EF	03	06 00	31 76	02 00	11 22	00 00	
HDMI 1 FORMAT	Set	AUTO	BE EF	03	06 00	BA 77	01 00	13 22	00 00
		VIDEO	BE EF	03	06 00	2A 76	01 00	13 22	01 00
		COMPUTER	BE EF	03	06 00	DA 76	01 00	13 22	02 00
	Get		BE EF	03	06 00	89 77	02 00	13 22	00 00
HDMI 2 FORMAT	Set	AUTO	BE EF	03	06 00	52 75	01 00	1D 22	00 00
		VIDEO	BE EF	03	06 00	C2 74	01 00	1D 22	01 00
		COMPUTER	BE EF	03	06 00	32 74	01 00	1D 22	02 00
	Get		BE EF	03	06 00	61 75	02 00	1D 22	00 00

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
DVI-D FORMAT	Set	AUTO	BE EF	03	06 00	62 74	01 00	19 22	00 00
		VIDEO	BE EF	03	06 00	F2 75	01 00	19 22	01 00
		COMPUTER	BE EF	03	06 00	02 75	01 00	19 22	02 00
	Get		BE EF	03	06 00	51 74	02 00	19 22	00 00
HDBaseT FORMAT	Set	AUTO	BE EF	03	06 00	7A EA	01 00	D3 20	00 00
		VIDEO	BE EF	03	06 00	EA EB	01 00	D3 20	01 00
		COMPUTER	BE EF	03	06 00	1A EB	01 00	D3 20	02 00
	Get		BE EF	03	06 00	49 EA	02 00	D3 20	00 00
HDMI 1 RANGE	Set	AUTO	BE EF	03	06 00	86 D8	01 00	22 20	00 00
		NORMAL	BE EF	03	06 00	16 D9	01 00	22 20	01 00
		ENHANCED	BE EF	03	06 00	E6 D9	01 00	22 20	02 00
	Get		BE EF	03	06 00	B5 D8	02 00	22 20	00 00
HDMI 2 RANGE	Set	AUTO	BE EF	03	06 00	7A D9	01 00	23 20	00 00
		NORMAL	BE EF	03	06 00	EA D8	01 00	23 20	01 00
		ENHANCED	BE EF	03	06 00	1A D8	01 00	23 20	02 00
	Get		BE EF	03	06 00	49 D9	02 00	23 20	00 00
DVI-D RANGE	Set	AUTO	BE EF	03	06 00	FE D4	01 00	20 20	10 00
		NORMAL	BE EF	03	06 00	3E D9	01 00	20 20	00 00
		ENHANCED	BE EF	03	06 00	AE D8	01 00	20 20	01 00
	Get		BE EF	03	06 00	0D D9	02 00	20 20	00 00
HDBaseT RANGE	Set	AUTO	BE EF	03	06 00	86 EB	01 00	D2 20	00 00
		NORMAL	BE EF	03	06 00	16 EA	01 00	D2 20	01 00
		ENHANCED	BE EF	03	06 00	E6 EA	01 00	D2 20	02 00
	Get		BE EF	03	06 00	B5 EB	02 00	D2 20	00 00
COMPUTER IN1	Set	AUTO	BE EF	03	06 00	CE D6	01 00	10 20	03 00
		SYNC ON G OFF	BE EF	03	06 00	5E D7	01 00	10 20	02 00
	Get		BE EF	03	06 00	0D D6	02 00	10 20	00 00
COMPUTER IN2	Set	AUTO	BE EF	03	06 00	32 D7	01 00	11 20	03 00
		SYNC ON G OFF	BE EF	03	06 00	A2 D6	01 00	11 20	02 00
	Get		BE EF	03	06 00	F1 D7	02 00	11 20	00 00
FRAME LOCK - COMPUTER IN1	Set	OFF	BE EF	03	06 00	3B C2	01 00	50 30	00 00
		ON	BE EF	03	06 00	AB C3	01 00	50 30	01 00
	Get		BE EF	03	06 00	08 C2	02 00	50 30	00 00
FRAME LOCK - COMPUTER IN2	Set	OFF	BE EF	03	06 00	0B C3	01 00	54 30	00 00
		ON	BE EF	03	06 00	9B C2	01 00	54 30	01 00
	Get		BE EF	03	06 00	38 C3	02 00	54 30	00 00
FRAME LOCK - HDMI 1	Set	OFF	BE EF	03	06 00	7F C2	01 00	53 30	00 00
		ON	BE EF	03	06 00	EF C3	01 00	53 30	01 00
	Get		BE EF	03	06 00	4C C2	02 00	53 30	00 00
FRAME LOCK - HDMI 2	Set	OFF	BE EF	03	06 00	97 C0	01 00	5D 30	00 00
		ON	BE EF	03	06 00	07 C1	01 00	5D 30	01 00
	Get		BE EF	03	06 00	A4 C0	02 00	5D 30	00 00
FRAME LOCK - DVI-D	Set	OFF	BE EF	03	06 00	A7 C1	01 00	59 30	00 00
		ON	BE EF	03	06 00	37 C0	01 00	59 30	01 00
	Get		BE EF	03	06 00	94 C1	02 00	59 30	00 00
FRAME LOCK - HDBaseT	Set	OFF	BE EF	03	06 00	C2 EB	01 00	D1 20	00 00
		ON	BE EF	03	06 00	52 EA	01 00	D1 20	01 00
	Get		BE EF	03	06 00	F1 EB	02 00	D1 20	00 00

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
GEOMETRIC MODE	Set	KEystone	BE EF 03 06 00	6B 8C	01 00	30 31 01 00
		PERFECT FIT	BE EF 03 06 00	9B 8C	01 00	30 31 02 00
		EDGE BLENDING	BE EF 03 06 00	0B 8D	01 00	30 31 03 00
		WARPING	BE EF 03 06 00	3B 8F	01 00	30 31 04 00
	Get		BE EF 03 06 00	C8 8D	02 00	30 31 00 00
KEystone V	Get		BE EF 03 06 00	B9 D3	02 00	07 20 00 00
	Increment		BE EF 03 06 00	DF D3	04 00	07 20 00 00
	Decrement		BE EF 03 06 00	0E D2	05 00	07 20 00 00
KEystone V Reset	Execute		BE EF 03 06 00	08 D0	06 00	0C 70 00 00
KEystone H	Get		BE EF 03 06 00	E9 D0	02 00	0B 20 00 00
	Increment		BE EF 03 06 00	8F D0	04 00	0B 20 00 00
	Decrement		BE EF 03 06 00	5E D1	05 00	0B 20 00 00
KEystone H Reset	Execute		BE EF 03 06 00	98 D8	06 00	20 70 00 00
PERFECT FIT Left Top - H	Get		BE EF 03 06 00	31 89	02 00	21 21 00 00
	Increment		BE EF 03 06 00	57 89	04 00	21 21 00 00
	Decrement		BE EF 03 06 00	86 88	05 00	21 21 00 00
PERFECT FIT Left Top - V	Get		BE EF 03 06 00	75 89	02 00	22 21 00 00
	Increment		BE EF 03 06 00	13 89	04 00	22 21 00 00
	Decrement		BE EF 03 06 00	C2 88	05 00	22 21 00 00
PERFECT FIT Right Top - H	Get		BE EF 03 06 00	89 88	02 00	23 21 00 00
	Increment		BE EF 03 06 00	EF 88	04 00	23 21 00 00
	Decrement		BE EF 03 06 00	3E 89	05 00	23 21 00 00
PERFECT FIT Right Top - V	Get		BE EF 03 06 00	FD 89	02 00	24 21 00 00
	Increment		BE EF 03 06 00	9B 89	04 00	24 21 00 00
	Decrement		BE EF 03 06 00	4A 88	05 00	24 21 00 00
PERFECT FIT Left Bottom - H	Get		BE EF 03 06 00	01 88	02 00	25 21 00 00
	Increment		BE EF 03 06 00	67 88	04 00	25 21 00 00
	Decrement		BE EF 03 06 00	B6 89	05 00	25 21 00 00
PERFECT FIT Left Bottom - V	Get		BE EF 03 06 00	45 88	02 00	26 21 00 00
	Increment		BE EF 03 06 00	23 88	04 00	26 21 00 00
	Decrement		BE EF 03 06 00	F2 89	05 00	26 21 00 00
PERFECT FIT Right Bottom - H	Get		BE EF 03 06 00	B9 89	02 00	27 21 00 00
	Increment		BE EF 03 06 00	DF 89	04 00	27 21 00 00
	Decrement		BE EF 03 06 00	0E 88	05 00	27 21 00 00
PERFECT FIT Right Bottom - V	Get		BE EF 03 06 00	AD 8A	02 00	28 21 00 00
	Increment		BE EF 03 06 00	CB 8A	04 00	28 21 00 00
	Decrement		BE EF 03 06 00	1A 8B	05 00	28 21 00 00
PERFECT FIT All Corners Reset	Execute		BE EF 03 06 00	D5 8A	06 00	29 21 00 00

Names	Operation Type	Header				Command Data		
						Action	Type	Setting code
PERFECT FIT Left Side Distortion	Get	BE EF	03	06 00	31 97	02 00	41 21	00 00
	Increment	BE EF	03	06 00	57 97	04 00	41 21	00 00
	Decrement	BE EF	03	06 00	86 96	05 00	41 21	00 00
PERFECT FIT Right Side Distortion	Get	BE EF	03	06 00	75 97	02 00	42 21	00 00
	Increment	BE EF	03	06 00	13 97	04 00	42 21	00 00
	Decrement	BE EF	03	06 00	C2 96	05 00	42 21	00 00
PERFECT FIT Top Side Distortion	Get	BE EF	03	06 00	FD 97	02 00	44 21	00 00
	Increment	BE EF	03	06 00	9B 97	04 00	44 21	00 00
	Decrement	BE EF	03	06 00	4A 96	05 00	44 21	00 00
PERFECT FIT Bottom Side Distortion	Get	BE EF	03	06 00	01 96	02 00	45 21	00 00
	Increment	BE EF	03	06 00	67 96	04 00	45 21	00 00
	Decrement	BE EF	03	06 00	B6 97	05 00	45 21	00 00
PERFECT FIT All Sides Reset	Execute	BE EF	03	06 00	3D 96	06 00	47 21	00 00
PERFECT FIT Memory Save-1	Execute	BE EF	03	06 00	29 95	06 00	48 21	00 00
PERFECT FIT Memory Save-2	Execute	BE EF	03	06 00	D5 94	06 00	49 21	00 00
PERFECT FIT Memory Save-3	Execute	BE EF	03	06 00	91 94	06 00	4A 21	00 00
PERFECT FIT Memory Load-1	Execute	BE EF	03	06 00	6D 95	06 00	4B 21	00 00
PERFECT FIT Memory Load-2	Execute	BE EF	03	06 00	19 94	06 00	4C 21	00 00
PERFECT FIT Memory Load-3	Execute	BE EF	03	06 00	E5 95	06 00	4D 21	00 00

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
EDGE BLENDING LEFT TOP H	Get		BE EF	03	06 00	A8 8F	02 00	38 31	00 00
	Increment		BE EF	03	06 00	CE 8F	04 00	38 31	00 00
	Decrement		BE EF	03	06 00	1F 8E	05 00	38 31	00 00
EDGE BLENDING LEFT TOP V	Get		BE EF	03	06 00	54 8E	02 00	39 31	00 00
	Increment		BE EF	03	06 00	32 8E	04 00	39 31	00 00
	Decrement		BE EF	03	06 00	E3 8F	05 00	39 31	00 00
EDGE BLENDING RIGHT TOP H	Get		BE EF	03	06 00	10 8E	02 00	3A 31	00 00
	Increment		BE EF	03	06 00	76 8E	04 00	3A 31	00 00
	Decrement		BE EF	03	06 00	A7 8F	05 00	3A 31	00 00
EDGE BLENDING RIGHT TOP V	Get		BE EF	03	06 00	EC 8F	02 00	3B 31	00 00
	Increment		BE EF	03	06 00	8A 8F	04 00	3B 31	00 00
	Decrement		BE EF	03	06 00	5B 8E	05 00	3B 31	00 00
EDGE BLENDING LEFT BOTTOM H	Get		BE EF	03	06 00	98 8E	02 00	3C 31	00 00
	Increment		BE EF	03	06 00	FE 8E	04 00	3C 31	00 00
	Decrement		BE EF	03	06 00	2F 8F	05 00	3C 31	00 00
EDGE BLENDING LEFT BOTTOM V	Get		BE EF	03	06 00	64 8F	02 00	3D 31	00 00
	Increment		BE EF	03	06 00	02 8F	04 00	3D 31	00 00
	Decrement		BE EF	03	06 00	D3 8E	05 00	3D 31	00 00
EDGE BLENDING RIGHT BOTTOM H	Get		BE EF	03	06 00	20 8F	02 00	3E 31	00 00
	Increment		BE EF	03	06 00	46 8F	04 00	3E 31	00 00
	Decrement		BE EF	03	06 00	97 8E	05 00	3E 31	00 00
EDGE BLENDING RIGHT BOTTOM V	Get		BE EF	03	06 00	DC 8E	02 00	3F 31	00 00
	Increment		BE EF	03	06 00	BA 8E	04 00	3F 31	00 00
	Decrement		BE EF	03	06 00	6B 8F	05 00	3F 31	00 00
EDGE BLENDING CORNER Reset	Execute		BE EF	03	06 00	B0 8D	06 00	31 31	00 00
EDGE BLENDING REGION Reset	Execute		BE EF	03	06 00	8C 96	06 00	40 31	00 00
EDGE BLENDING LEVEL	Set	NORMAL	BE EF	03	06 00	C7 96	01 00	41 31	00 00
		BRIGHT	BE EF	03	06 00	57 97	01 00	41 31	01 00
		DARK	BE EF	03	06 00	A7 97	01 00	41 31	02 00
	Get		BE EF	03	06 00	F4 96	02 00	41 31	00 00
EDGE BLENDING LEFT	Get		BE EF	03	06 00	68 95	02 00	48 31	00 00
	Increment		BE EF	03	06 00	0E 95	04 00	48 31	00 00
	Decrement		BE EF	03	06 00	DF 94	05 00	48 31	00 00
EDGE BLENDING RIGHT	Get		BE EF	03	06 00	94 94	02 00	49 31	00 00
	Increment		BE EF	03	06 00	F2 94	04 00	49 31	00 00
	Decrement		BE EF	03	06 00	23 95	05 00	49 31	00 00

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
EDGE BLENDING TOP	Get		BE EF	03	06 00	D0 94	02 00	4A 31	00 00
	Increment		BE EF	03	06 00	B6 94	04 00	4A 31	00 00
	Decrement		BE EF	03	06 00	67 95	05 00	4A 31	00 00
EDGE BLENDING BOTTOM	Get		BE EF	03	06 00	2C 95	02 00	4B 31	00 00
	Increment		BE EF	03	06 00	4A 95	04 00	4B 31	00 00
	Decrement		BE EF	03	06 00	9B 94	05 00	4B 31	00 00
CROPPING MODE	Set	OFF	BE EF	03	06 00	FB 93	01 00	50 31	00 00
		ON	BE EF	03	06 00	6B 92	01 00	50 31	01 00
	Get		BE EF	03	06 00	C8 93	02 00	50 31	00 00
CROPPING SETUP X	Get		BE EF	03	06 00	A8 91	02 00	58 31	00 00
	Increment		BE EF	03	06 00	CE 91	04 00	58 31	00 00
	Decrement		BE EF	03	06 00	1F 90	05 00	58 31	00 00
CROPPING SETUP Y	Get		BE EF	03	06 00	54 90	02 00	59 31	00 00
	Increment		BE EF	03	06 00	32 90	04 00	59 31	00 00
	Decrement		BE EF	03	06 00	E3 91	05 00	59 31	00 00
CROPPING SETUP W	Get		BE EF	03	06 00	10 90	02 00	5A 31	00 00
	Increment		BE EF	03	06 00	76 90	04 00	5A 31	00 00
	Decrement		BE EF	03	06 00	A7 91	05 00	5A 31	00 00
CROPPING SETUP H	Get		BE EF	03	06 00	EC 91	02 00	5B 31	00 00
	Increment		BE EF	03	06 00	8A 91	04 00	5B 31	00 00
	Decrement		BE EF	03	06 00	5B 90	05 00	5B 31	00 00
CROPPING Apply	Execute		BE EF	03	06 00	B0 93	06 00	51 31	00 00
CROPPING Reset	Execute		BE EF	03	06 00	F4 93	06 00	52 31	00 00
WARPING MODE	Set	OFF	BE EF	03	06 00	FB 9C	01 00	60 31	00 00
		MODE-1	BE EF	03	06 00	6B 9D	01 00	60 31	01 00
		MODE-2	BE EF	03	06 00	9B 9D	01 00	60 31	02 00
		MODE-3	BE EF	03	06 00	0B 9C	01 00	60 31	03 00
	Get		BE EF	03	06 00	C8 9C	02 00	60 31	00 00

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
ECO MODE	Set	NORMAL	BE EF 03 06 00	3B 23	01 00	00 33
		ECO	BE EF 03 06 00	AB 22	01 00	00 33
	Get		BE EF 03 06 00	08 23	02 00	00 33
INSTALLATION	Set	FRONT / DESKTOP	BE EF 03 06 00	C7 D2	01 00	01 30
		REAR / DESKTOP	BE EF 03 06 00	57 D3	01 00	01 30
		REAR / CEILING	BE EF 03 06 00	A7 D3	01 00	01 30
		FRONT / CEILING	BE EF 03 06 00	37 D2	01 00	01 30
	Get		BE EF 03 06 00	F4 D2	02 00	01 30
STANDBY MODE	Set	NORMAL	BE EF 03 06 00	D6 D2	01 00	01 60
		SAVING	BE EF 03 06 00	46 D3	01 00	01 60
	Get		BE EF 03 06 00	E5 D2	02 00	01 60
MONITOR OUT - COMPUTER IN1	Set	COMPUTER IN1	BE EF 03 06 00	3E F4	01 00	B0 20
		COMPUTER IN2	BE EF 03 06 00	FE F6	01 00	B0 20
		OFF	BE EF 03 06 00	CE B5	01 00	B0 20
	Get		BE EF 03 06 00	0D F4	02 00	B0 20
MONITOR OUT - COMPUTER IN2	Set	COMPUTER IN1	BE EF 03 06 00	0E F5	01 00	B4 20
		COMPUTER IN2	BE EF 03 06 00	CE F7	01 00	B4 20
		OFF	BE EF 03 06 00	FE B4	01 00	B4 20
	Get		BE EF 03 06 00	3D F5	02 00	B4 20
MONITOR OUT - LAN	Set	COMPUTER IN1	BE EF 03 06 00	1A F6	01 00	BB 20
		COMPUTER IN2	BE EF 03 06 00	DA F4	01 00	BB 20
		OFF	BE EF 03 06 00	EA B7	01 00	BB 20
	Get		BE EF 03 06 00	29 F6	02 00	BB 20
MONITOR OUT - HDMI 1	Set	COMPUTER IN1	BE EF 03 06 00	7A F4	01 00	B3 20
		COMPUTER IN2	BE EF 03 06 00	BA F6	01 00	B3 20
		OFF	BE EF 03 06 00	8A B5	01 00	B3 20
	Get		BE EF 03 06 00	49 F4	02 00	B3 20
MONITOR OUT - HDMI 2	Set	COMPUTER IN1	BE EF 03 06 00	92 F6	01 00	BD 20
		COMPUTER IN2	BE EF 03 06 00	52 F4	01 00	BD 20
		OFF	BE EF 03 06 00	62 B7	01 00	BD 20
	Get		BE EF 03 06 00	A1 F6	02 00	BD 20
MONITOR OUT - DVI-D	Set	COMPUTER IN1	BE EF 03 06 00	A2 F7	01 00	B9 20
		COMPUTER IN2	BE EF 03 06 00	62 F5	01 00	B9 20
		OFF	BE EF 03 06 00	52 B6	01 00	B9 20
	Get		BE EF 03 06 00	91 F7	02 00	B9 20
MONITOR OUT - HDBaseT	Set	COMPUTER IN1	BE EF 03 06 00	3E EA	01 00	D0 20
		COMPUTER IN2	BE EF 03 06 00	FE E8	01 00	D0 20
		OFF	BE EF 03 06 00	CE AB	01 00	D0 20
	Get		BE EF 03 06 00	0D EA	02 00	D0 20
MONITOR OUT - VIDEO	Set	COMPUTER IN1	BE EF 03 06 00	C2 F5	01 00	B1 20
		COMPUTER IN2	BE EF 03 06 00	02 F7	01 00	B1 20
		OFF	BE EF 03 06 00	32 B4	01 00	B1 20
	Get		BE EF 03 06 00	F1 F5	02 00	B1 20
MONITOR OUT - STANDBY	Set	COMPUTER IN1	BE EF 03 06 00	2A F7	01 00	BF 20
		COMPUTER IN2	BE EF 03 06 00	EA F5	01 00	BF 20
		OFF	BE EF 03 06 00	DA B6	01 00	BF 20
	Get		BE EF 03 06 00	19 F7	02 00	BF 20

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
LANGUAGE	Set	ENGLISH	BE EF 03 06 00	F7 D3	01 00	05 30 00 00
		FRANÇAIS	BE EF 03 06 00	67 D2	01 00	05 30 01 00
		DEUTSCH	BE EF 03 06 00	97 D2	01 00	05 30 02 00
		ESPAÑOL	BE EF 03 06 00	07 D3	01 00	05 30 03 00
		ITALIANO	BE EF 03 06 00	37 D1	01 00	05 30 04 00
		NORSK	BE EF 03 06 00	A7 D0	01 00	05 30 05 00
		NEDERLANDS	BE EF 03 06 00	57 D0	01 00	05 30 06 00
		PORTUGUÊS	BE EF 03 06 00	C7 D1	01 00	05 30 07 00
		日本語	BE EF 03 06 00	37 D4	01 00	05 30 08 00
		簡体中文	BE EF 03 06 00	A7 D5	01 00	05 30 09 00
		繁体中文	BE EF 03 06 00	37 DE	01 00	05 30 10 00
		한국어	BE EF 03 06 00	57 D5	01 00	05 30 0A 00
		SVENSKA	BE EF 03 06 00	C7 D4	01 00	05 30 0B 00
		РУССКИЙ	BE EF 03 06 00	F7 D6	01 00	05 30 0C 00
		SUOMI	BE EF 03 06 00	67 D7	01 00	05 30 0D 00
		POLSKI	BE EF 03 06 00	97 D7	01 00	05 30 0E 00
		TÜRKÇE	BE EF 03 06 00	07 D6	01 00	05 30 0F 00
		DANSK	BE EF 03 06 00	A7 DF	01 00	05 30 11 00
		ČESKY	BE EF 03 06 00	57 DF	01 00	05 30 12 00
		MAGYAR	BE EF 03 06 00	C7 DE	01 00	05 30 13 00
		ROMÂNĂ	BE EF 03 06 00	F7 DC	01 00	05 30 14 00
		SLOVENSKI	BE EF 03 06 00	67 DD	01 00	05 30 15 00
		HRVATSKI	BE EF 03 06 00	97 DD	01 00	05 30 16 00
		ΕΛΛΗΝΙΚΑ	BE EF 03 06 00	07 DC	01 00	05 30 17 00
		LIETUVIŲ	BE EF 03 06 00	F7 D9	01 00	05 30 18 00
		EESTI	BE EF 03 06 00	67 D8	01 00	05 30 19 00
		LATVIEŠU	BE EF 03 06 00	97 D8	01 00	05 30 1A 00
		ไทย	BE EF 03 06 00	07 D9	01 00	05 30 1B 00
		دے برع لاء غل لاء	BE EF 03 06 00	37 DB	01 00	05 30 1C 00
		اے سراف	BE EF 03 06 00	A7 DA	01 00	05 30 1D 00
		PORTUGUÊS BRA	BE EF 03 06 00	57 DA	01 00	05 30 1E 00
		BAHASA IND	BE EF 03 06 00	C7 DB	01 00	05 30 1F 00
		TIENG VIET	BE EF 03 06 00	37 CA	01 00	05 30 20 00
	NOTE) Not all of the languages in this table are supported.					
	Get	BE EF 03 06 00	C4 D3	02 00	05 30	00 00

Names	Operation Type	Header			CRC	Command Data		
						Action	Type	Setting code
MENU POSITION V	Get	BE EF	03	06 00	40 D7	02 00	16 30	00 00
	Increment	BE EF	03	06 00	26 D7	04 00	16 30	00 00
	Decrement	BE EF	03	06 00	F7 D6	05 00	16 30	00 00
MENU POSITION V Reset	Execute	BE EF	03	06 00	A8 C7	06 00	44 70	00 00
MENU POSITION H	Get	BE EF	03	06 00	04 D7	02 00	15 30	00 00
	Increment	BE EF	03	06 00	62 D7	04 00	15 30	00 00
	Decrement	BE EF	03	06 00	B3 D6	05 00	15 30	00 00
MENU POSITION H Reset	Execute	BE EF	03	06 00	DC C6	06 00	43 70	00 00
BLANK	Set	MyScreen	BE EF	03	06 00	FB CA	01 00	00 30
		ORIGINAL	BE EF	03	06 00	FB E2	01 00	00 30
		BLUE	BE EF	03	06 00	CB D3	01 00	00 30
		WHITE	BE EF	03	06 00	6B D0	01 00	00 30
		BLACK	BE EF	03	06 00	9B D0	01 00	00 30
BLANK On/Off	Set	Get	BE EF	03	06 00	08 D3	02 00	00 30
		OFF	BE EF	03	06 00	FB D8	01 00	20 30
		ON	BE EF	03	06 00	6B D9	01 00	20 30
	Get	BE EF	03	06 00	C8 D8	02 00	20 30	00 00
AUTO BLANK	Set	BLUE	BE EF	03	06 00	67 D1	01 00	0D 30
		WHITE	BE EF	03	06 00	C7 D2	01 00	0D 30
		BLACK	BE EF	03	06 00	37 D2	01 00	0D 30
	Get	BE EF	03	06 00	A4 D1	02 00	0D 30	00 00
START UP	Set	MyScreen	BE EF	03	06 00	CB CB	01 00	04 30
		ORIGINAL	BE EF	03	06 00	0B D2	01 00	04 30
		OFF	BE EF	03	06 00	9B D3	01 00	04 30
	Get	BE EF	03	06 00	38 D2	02 00	04 30	00 00

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
MyScreen Lock	Set	OFF	BE EF 03 06 00	3B EF	01 00	C0 30 00 00
		ON	BE EF 03 06 00	AB EE	01 00	C0 30 01 00
	Get		BE EF 03 06 00	08 EF	02 00	C0 30 00 00
OSD MESSAGE	Set	SILENT	BE EF 03 06 00	8F D6	01 00	17 30 00 00
		NORMAL	BE EF 03 06 00	1F D7	01 00	17 30 01 00
		INHIBIT	BE EF 03 06 00	EF D7	01 00	17 30 02 00
	Get		BE EF 03 06 00	BC D6	02 00	17 30 00 00
TEMPLATE	Set	TEST PATTERN	BE EF 03 06 00	43 D9	01 00	22 30 00 00
		DOT-LINE 1	BE EF 03 06 00	D3 D8	01 00	22 30 01 00
		DOT-LINE 2	BE EF 03 06 00	23 D8	01 00	22 30 02 00
		DOT-LINE 3	BE EF 03 06 00	B3 D9	01 00	22 30 03 00
		DOT-LINE 4	BE EF 03 06 00	83 DB	01 00	22 30 04 00
		CIRCLE 1	BE EF 03 06 00	13 DA	01 00	22 30 05 00
		CIRCLE 2	BE EF 03 06 00	E3 DA	01 00	22 30 06 00
		MAP 1	BE EF 03 06 00	83 D4	01 00	22 30 10 00
		MAP 2	BE EF 03 06 00	13 D5	01 00	22 30 11 00
	Get		BE EF 03 06 00	83 C0	01 00	22 30 20 00
TEMPLATE On/Off	Set	OFF	BE EF 03 06 00	70 D9	02 00	22 30 00 00
		ON	BE EF 03 06 00	2F D9	01 00	23 30 01 00
	Get		BE EF 03 06 00	8C D8	02 00	23 30 00 00
C. C. - DISPLAY	Set	OFF	BE EF 03 06 00	FA 62	01 00	00 37 00 00
		ON	BE EF 03 06 00	6A 63	01 00	00 37 01 00
	Get		BE EF 03 06 00	C9 62	02 00	00 37 00 00
C. C. - MODE	Set	CAPTIONS	BE EF 03 06 00	06 63	01 00	01 37 00 00
		TEXT	BE EF 03 06 00	96 62	01 00	01 37 01 00
	Get		BE EF 03 06 00	35 63	02 00	01 37 00 00
C. C. - CHANNEL	Set	1	BE EF 03 06 00	D2 62	01 00	02 37 01 00
		2	BE EF 03 06 00	22 62	01 00	02 37 02 00
		3	BE EF 03 06 00	B2 63	01 00	02 37 03 00
		4	BE EF 03 06 00	82 61	01 00	02 37 04 00
	Get		BE EF 03 06 00	71 63	02 00	02 37 00 00
SOURCE SKIP - COMPUTER IN1	Set	NORMAL	BE EF 03 06 00	FE 78	01 00	20 22 00 00
		SKIP	BE EF 03 06 00	6E 79	01 00	20 22 01 00
	Get		BE EF 03 06 00	CD 78	02 00	20 22 00 00
SOURCE SKIP - COMPUTER IN2	Set	NORMAL	BE EF 03 06 00	CE 79	01 00	24 22 00 00
		SKIP	BE EF 03 06 00	5E 78	01 00	24 22 01 00
	Get		BE EF 03 06 00	FD 79	02 00	24 22 00 00
SOURCE SKIP - LAN	Set	NORMAL	BE EF 03 06 00	DA 7A	01 00	2B 22 00 00
		SKIP	BE EF 03 06 00	4A 7B	01 00	2B 22 01 00
	Get		BE EF 03 06 00	E9 7A	02 00	2B 22 00 00

RS-232C Communication / Network command table (continued)

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
SOURCE SKIP - HDMI 1	Set	NORMAL	BE EF	03	06 00	BA 78	01 00	23 22	00 00
		SKIP	BE EF	03	06 00	2A 79	01 00	23 22	01 00
	Get		BE EF	03	06 00	89 78	02 00	23 22	00 00
SOURCE SKIP - HDMI 2	Set	NORMAL	BE EF	03	06 00	52 7A	01 00	2D 22	00 00
		SKIP	BE EF	03	06 00	C2 7B	01 00	2D 22	01 00
	Get		BE EF	03	06 00	61 7A	02 00	2D 22	00 00
SOURCE SKIP DVI-D	Set	NORMAL	BE EF	03	06 00	62 7B	01 00	29 22	00 00
		SKIP	BE EF	03	06 00	F2 7A	01 00	29 22	01 00
	Get		BE EF	03	06 00	51 7B	02 00	29 22	00 00
SOURCE SKIP HDBaseT	Set	NORMAL	BE EF	03	06 00	B6 EA	01 00	D6 20	00 00
		SKIP	BE EF	03	06 00	26 EB	01 00	D6 20	01 00
	Get		BE EF	03	06 00	85 EA	02 00	D6 20	00 00
SOURCE SKIP - VIDEO	Set	NORMAL	BE EF	03	06 00	02 79	01 00	21 22	00 00
		SKIP	BE EF	03	06 00	92 78	01 00	21 22	01 00
	Get		BE EF	03	06 00	31 79	02 00	21 22	00 00
AUTO SEARCH	Set	OFF	BE EF	03	06 00	B6 D6	01 00	16 20	00 00
		ON	BE EF	03	06 00	26 D7	01 00	16 20	01 00
	Get		BE EF	03	06 00	85 D6	02 00	16 20	00 00
DIRECT POWER ON	Set	OFF	BE EF	03	06 00	3B 89	01 00	20 31	00 00
		ON	BE EF	03	06 00	AB 88	01 00	20 31	01 00
	Get		BE EF	03	06 00	08 89	02 00	20 31	00 00
AUTO POWER OFF	Get		BE EF	03	06 00	08 86	02 00	10 31	00 00
		Increment	BE EF	03	06 00	6E 86	04 00	10 31	00 00
		Decrement	BE EF	03	06 00	BF 87	05 00	10 31	00 00
SHUTTER TIMER	Set	1h	BE EF	03	06 00	27 92	01 00	06 24	01 00
		3h	BE EF	03	06 00	47 93	01 00	06 24	03 00
		6h	BE EF	03	06 00	17 90	01 00	06 24	06 00
	Get		BE EF	03	06 00	84 93	02 00	06 24	00 00
LAMP MODE	Set	DUAL	BE EF	03	06 00	1F 21	01 00	0B 33	00 00
		LAMP-1	BE EF	03	06 00	8F 20	01 00	0B 33	01 00
		LAMP-2	BE EF	03	06 00	7F 20	01 00	0B 33	02 00
		ALTERNATE	BE EF	03	06 00	DF 2C	01 00	0B 33	10 00
	Get		BE EF	03	06 00	2C 21	02 00	0B 33	00 00
ALTERNATE	Set	AUTO	BE EF	03	06 00	6B 20	01 00	0C 33	00 00
		CYCLE	BE EF	03	06 00	FB 21	01 00	0C 33	01 00
	Get		BE EF	03	06 00	58 20	02 00	0C 33	00 00
CYCLE TIME	Set	6h	BE EF	03	06 00	37 22	01 00	0D 33	06 00
		12h	BE EF	03	06 00	97 24	01 00	0D 33	0C 00
		18h	BE EF	03	06 00	37 2D	01 00	0D 33	12 00
		24h	BE EF	03	06 00	97 2B	01 00	0D 33	18 00
		1WEEK	BE EF	03	06 00	57 5E	01 00	0D 33	A8 00
	Get		BE EF	03	06 00	A4 21	02 00	0D 33	00 00

Names	Operation Type		Header			CRC	Command Data		
							Action	Type	Setting code
LAMP-1 TIME Lower Bytes	Get		BE EF	03	06 00	C2 FF	02 00	90 10	00 00
LAMP-1 TIME Higher Bytes	Get		BE EF	03	06 00	2A FD	02 00	9E 10	00 00
LAMP-1 TIME Reset	Execute		BE EF	03	06 00	58 DC	06 00	30 70	00 00
LAMP-2 TIME Lower Bytes	Get		BE EF	03	06 00	02 AE	02 00	90 11	00 00
LAMP-2 TIME Higher Bytes	Get		BE EF	03	06 00	FE AF	02 00	91 11	00 00
LAMP-2 TIME Reset	Execute		BE EF	03	06 00	68 DD	06 00	34 70	00 00
FILTER TIME Lower Bytes	Get		BE EF	03	06 00	C2 F0	02 00	A0 10	00 00
FILTER TIME Higher Bytes	Get		BE EF	03	06 00	D6 FC	02 00	9F 10	00 00
FILTER TIME Reset	Execute		BE EF	03	06 00	98 C6	06 00	40 70	00 00
MY BUTTON-1	Set	MY IMAGE	BE EF	03	06 00	5A 3D	01 00	00 36	16 00
		MESSENGER	BE EF	03	06 00	AA 29	01 00	00 36	25 00
		INFORMATION	BE EF	03	06 00	FA 3E	01 00	00 36	10 00
		MY MEMORY	BE EF	03	06 00	9A 3F	01 00	00 36	12 00
		ACTIVE IRIS	BE EF	03	06 00	AA 3D	01 00	00 36	15 00
		FILTER RESET	BE EF	03	06 00	3A 3C	01 00	00 36	14 00
		TEMPLATE	BE EF	03	06 00	CA 39	01 00	00 36	1B 00
		PbyP/PinP SWAP	BE EF	03	06 00	5A 38	01 00	00 36	1A 00
		PinP POSITION	BE EF	03	06 00	3A 22	01 00	00 36	3C 00
		RESOLUTION	BE EF	03	06 00	9A 3A	01 00	00 36	1E 00
		STATUS MONITOR	BE EF	03	06 00	0A 20	01 00	00 36	3B 00
		BLANK	BE EF	03	06 00	FA 02	01 00	00 36	40 00
		Get	BE EF	03	06 00	09 33	02 00	00 36	00 00
MY BUTTON-2	Set	MY IMAGE	BE EF	03	06 00	A6 3C	01 00	01 36	16 00
		MESSENGER	BE EF	03	06 00	56 28	01 00	01 36	25 00
		INFORMATION	BE EF	03	06 00	06 3F	01 00	01 36	10 00
		MY MEMORY	BE EF	03	06 00	66 3E	01 00	01 36	12 00
		ACTIVE IRIS	BE EF	03	06 00	56 3C	01 00	01 36	15 00
		FILTER RESET	BE EF	03	06 00	C6 3D	01 00	01 36	14 00
		TEMPLATE	BE EF	03	06 00	36 38	01 00	01 36	1B 00
		PbyP/PinP SWAP	BE EF	03	06 00	A6 39	01 00	01 36	1A 00
		PinP POSITION	BE EF	03	06 00	C6 23	01 00	01 36	3C 00
		RESOLUTION	BE EF	03	06 00	66 3B	01 00	01 36	1E 00
		STATUS MONITOR	BE EF	03	06 00	F6 21	01 00	01 36	3B 00
		BLANK	BE EF	03	06 00	06 03	01 00	01 36	40 00
		Get	BE EF	03	06 00	F5 32	02 00	01 36	00 00

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
MY BUTTON-3	Set	MY IMAGE	BE EF 03 06 00	E2 3C	01 00	02 36 16 00
		MESSENGER	BE EF 03 06 00	12 28	01 00	02 36 25 00
		INFORMATION	BE EF 03 06 00	42 3F	01 00	02 36 10 00
		MY MEMORY	BE EF 03 06 00	22 3E	01 00	02 36 12 00
		ACTIVE IRIS	BE EF 03 06 00	12 3C	01 00	02 36 15 00
		FILTER RESET	BE EF 03 06 00	82 3D	01 00	02 36 14 00
		TEMPLATE	BE EF 03 06 00	72 38	01 00	02 36 1B 00
		PbyP/PinP SWAP	BE EF 03 06 00	E2 39	01 00	02 36 1A 00
		PinP POSITION	BE EF 03 06 00	82 23	01 00	02 36 3C 00
		RESOLUTION	BE EF 03 06 00	22 3B	01 00	02 36 1E 00
		STATUS MONITOR	BE EF 03 06 00	B2 21	01 00	02 36 3B 00
		BLANK	BE EF 03 06 00	42 03	01 00	02 36 40 00
MY BUTTON-4	Get		BE EF 03 06 00	B1 32	02 00	02 36 00 00
	Set	MY IMAGE	BE EF 03 06 00	1E 3D	01 00	03 36 16 00
		MESSENGER	BE EF 03 06 00	EE 29	01 00	03 36 25 00
		INFORMATION	BE EF 03 06 00	BE 3E	01 00	03 36 10 00
		MY MEMORY	BE EF 03 06 00	DE 3F	01 00	03 36 12 00
		ACTIVE IRIS	BE EF 03 06 00	EE 3D	01 00	03 36 15 00
		FILTER RESET	BE EF 03 06 00	7E 3C	01 00	03 36 14 00
		TEMPLATE	BE EF 03 06 00	8E 39	01 00	03 36 1B 00
		PbyP/PinP SWAP	BE EF 03 06 00	1E 38	01 00	03 36 1A 00
		PinP POSITION	BE EF 03 06 00	7E 22	01 00	03 36 3C 00
		RESOLUTION	BE EF 03 06 00	DE 3A	01 00	03 36 1E 00
		STATUS MONITOR	BE EF 03 06 00	4E 20	01 00	03 36 3B 00
		BLANK	BE EF 03 06 00	BE 02	01 00	03 36 40 00
	Get		BE EF 03 06 00	4D 33	02 00	03 36 00 00

Names	Operation Type	Header	CRC	Command Data		
				Action	Type	Setting code
REMOTE RECEIV. FRONT	Set	OFF	BE EF 03 06 00	FF 32	01 00 00 26	00 00
		ON	BE EF 03 06 00	6F 33	01 00 00 26	01 00
	Get		BE EF 03 06 00	CC 32	02 00 00 26	00 00
REMOTE RECEIV. REAR	Set	OFF	BE EF 03 06 00	03 33	01 00 01 26	00 00
		ON	BE EF 03 06 00	93 32	01 00 01 26	01 00
	Get		BE EF 03 06 00	30 33	02 00 01 26	00 00
REMOTE HDBaseT	Set	OFF	BE EF 03 06 00	BB 32	01 00 03 26	00 00
		ON	BE EF 03 06 00	2B 33	01 00 03 26	01 00
	Get		BE EF 03 06 00	88 32	02 00 03 26	00 00
REMOTE FREQ. NORMAL	Set	OFF	BE EF 03 06 00	FF 3D	01 00 30 26	00 00
		ON	BE EF 03 06 00	6F 3C	01 00 30 26	01 00
	Get		BE EF 03 06 00	CC 3D	02 00 30 26	00 00
REMOTE FREQ. HIGH	Set	OFF	BE EF 03 06 00	03 3C	01 00 31 26	00 00
		ON	BE EF 03 06 00	93 3D	01 00 31 26	01 00
	Get		BE EF 03 06 00	30 3C	02 00 31 26	00 00
REMOTE ID	Set	ALL	BE EF 03 06 00	9F 30	01 00 08 26	00 00
		1	BE EF 03 06 00	0F 31	01 00 08 26	01 00
		2	BE EF 03 06 00	FF 31	01 00 08 26	02 00
		3	BE EF 03 06 00	6F 30	01 00 08 26	03 00
		4	BE EF 03 06 00	5F 32	01 00 08 26	04 00
	Get		BE EF 03 06 00	AC 30	02 00 08 26	00 00
MY IMAGE	Set	OFF	BE EF 03 06 00	3A C3	01 00 00 35	00 00
		IMAGE-1	BE EF 03 06 00	AA C2	01 00 00 35	01 00
		IMAGE-2	BE EF 03 06 00	5A C2	01 00 00 35	02 00
		IMAGE-3	BE EF 03 06 00	CA C3	01 00 00 35	03 00
		IMAGE-4	BE EF 03 06 00	FA C1	01 00 00 35	04 00
	Get		BE EF 03 06 00	09 C3	02 00 00 35	00 00
MY IMAGE IMAGE-1 Delete	Execute		BE EF 03 06 00	71 C3	06 00 01 35	00 00
MY IMAGE IMAGE-2 Delete	Execute		BE EF 03 06 00	35 C3	06 00 02 35	00 00
MY IMAGE IMAGE-3 Delete	Execute		BE EF 03 06 00	C9 C2	06 00 03 35	00 00
MY IMAGE IMAGE-4 Delete	Execute		BE EF 03 06 00	BD C3	06 00 04 35	00 00

PJLink command

Commands	Control Description	Parameter or Response
POWR	Power Control	0 = Standby 1 = Power On
POWR ?	Power Status inquiry	0 = Standby 1 = Power On 2 = Cool Down
INPT	Input Source selection	11 = COMPUTER IN1 12 = COMPUTER IN2 23 = VIDEO 31 = HDMI 1 32 = DVI-D 33 = HDMI 2 36 = HDBaseT 51 = LAN
INPT ?	Input Source inquiry	11 = COMPUTER IN1 12 = COMPUTER IN2 23 = VIDEO 31 = HDMI 1 32 = DVI-D 33 = HDMI 2 36 = HDBaseT 51 = LAN
AVMT	AV Mute	30 = AV Mute off 31 = AV Mute on
AVMT ?	AV Mute inquiry	30 = AV Mute off 31 = AV Mute on
ERST ?	Error Status inquiry	1st byte: Refers to Fan error; one of 0 to 2 2nd byte: Refers to Lamp error; one of 0 to 2 3rd byte: Refers to Temperature error; one of 0 to 2 4th byte: Refers to Cover error; one of 0 to 2 5th byte: Refers to Filter error; one of 0 to 2 6th byte: Refers to Other error; one of 0 to 2 The meaning of 0 to 2 is as given below 0 = Error is not detected; 1 = Warning; 2 = Error
LAMP ?	Lamp Status inquiry	1st number (digits 1 to 5): Lamp Time 2nd number : 0 = Lamp off, 1 = Lamp on
INST ?	Input Source List inquiry	11 12 23 31 32 33 36 51
NAME ?	Projector Name inquiry	Responds with the name set in the item PROJECTOR NAME of the NETWORK menu

Commands	Control Description	Parameter or Response
INF1 ?	Manufacturer's Name inquiry	HITACHI
INF2 ?	Model Name inquiry	CP-X9110 CP-WX9210 CP-WU9410
INFO ?	Other Information inquiry	Responds with the factory information and so on
CLSS ?	Class Information inquiry	1

NOTE • The password used in PJLink™ is the same as the password set in the Web Control. To use PJLink™ without authentication, do not set any password in Web Browser Control.

• For specifications of PJLink™, see the web site of the Japan Business Machine and Information System Industries Association.

URL: <http://pjlink.jbmia.or.jp/>